AOMWAY Video Transmitter Packs 200mW

The Aomway Mini video transmitter packs 200mW of ultra clean 5.8GHz power in a micro sized video/audio package! A must have for those looking to save size and weight while still getting good performance. The Aowmay is transmitting a full range of 32 channels and only weighs 6g. It's perfect for a wide range of aircraft, especially small models and 350 size multi-rotors such as Quanum Nova, DJI Phantom, QR X350 and more!

Features:

• Micro sized and light weight - perfect for use with small models

• 32 channels: Cover A, B, E bands and F bands

• Transmitter frequency: 5645-5945MHz with 200mW power output

• Transmitting distance $> \sim 1500$ m (open area)

Modulate: Wideband FM Modulate Weight: 6g (without antenna)

Video Format: NTSC/PAL

Output Impedance: 50 Ohm Included:

Output Power: 23~24dBm Aowmay 5.GHz 200mW 32CH A/V

Channel: 32CH transmitter

Operating Voltage: 7V~24V

A/V cable and Power cable

Supply Current: 190mA

3dbi Omni antenna

Operating Temperature: -10~85 Video

Band Width: 0~8.0 MHz

Audio Carrier Frequency: 6.5MHz

Video Input Level: 0.8~1.2 Vp-p

Video Input Impedance: 75 Ohm

Audio Input Level: 0.5~2.0 Vp-p

Audio Input Impedance: 10K Ohm

Connector: SMA (NOT RP)

Dimension: 26mm x 23mm x 8mm